



With the mains connector, PackBot EOD users can operate the control console (PCC) from mains without having to rely on the system batteries.

The kit consists of:

1 off Desktop mains adapter with mains cable

Input: 100V-240V, 47-63Hz, 3.2A, IEC

Output: 24V DC, 5.41A, 130W max.

Connector to PCC: Fischer 104, 11-pins

The mains adapter carries the GS seal according to the German device safety law.

The device carries the CE-label according to CE Directive 93/68/EEC and is UL-listed.

The mains connectors is designed and manufactured to meet:

- Electric Safety acc. to Low Voltage Directive 73/23/EEC:
EN60950:1992 + /A1:1993 /A2:1993 /A3:1995 /A4:1997 /A11:1997
- EMV acc. to EMC-Directive 89/336/EEC:
EN50081-1:1992
(EN550022B:1998, EN61000-3-2:1995 +/A1:1998 /A2:1998 /A14:2000, EN61000-3-3:1995)
EN50082-1:1997
(EN61000-4-2:1995, -4-3:1996, -4-4:1995, -4-6:1996, -4-8:1994, -4-11:1994)
EN55024:1998
(EN61000-4-2:1995, -4-3:1996, -4-4:1995, -4-6:1996, -4-8:1994, -4-11:1994)
- ROHS acc. to 2002/95/EC

Specifications are subject to change without notice.

